

EM-269A

Sterownik silników BLDC

EM-269A

Sterownik silnika BLDC, 2Q, 12-35V DC, 2A



- 12-24 V DC, 2 A prąd ciągły, 3 A prąd szczytowy
- Praca w pętli otwartej lub zamkniętej (sprężenie zwrotne z czujników Halla)
- Praca dwukwadrantowa
- Kompaktowa budowa, montaż na szynie DIN

OPIS PRODUKTU

EM-269A is brushless DC-motor driver for motors with hall sensor feedback. The unit has a mosfet power stage with good efficiency and it meets also today's EMC requirements. The unit has the basic digital command inputs like direction, start/stop, and analog input for speed control. Device has one NPN output for fault and overcurrent indication use. Indication output functions can be defined with parameter. The fault situations are also indicated with on-board LED.

There are two control options for speed. Direct control (open loop) sets motor voltage in proportion to control voltage as with a standard DC-motor. Closed loop mode uses hall sensor feedback for speed control. This mode offers good speed regulation. Start and stop ramps are working in both mode. Speed adjust range, closed loop rpm range and ramps can be set with parameters. Analog input is filtered, so that also PWM signal of PLC can be used to control speed.

Parameter setting can be done digitally with EM-236 interface unit or with Emen-Tool lite PC-program and EM-268 adapter. There is also an option to use iPhone with Emmentool-APP and EM-326 adapter. The Parameters setting are stored into driver's nonvolatile memory .

The parameter interfaces can be also used for motor current monitoring.

Driver card can be installed in DIN-rail base and some enclosure options are also available.

FEATURES

- Three phase output
- Speed adjustment
- Current limit and trip.
- Open/closed loop modes
- Settable Indication output
- Good efficiency
- Low EMC emissions
- DIN-rail mountable

SPECYFIKACJA TECHNICZNA

Częstotliwość PWM	16kHz
Dimensions length x width x height	72x32x18 mm
Dostawca	Electromen
Maksymalny prąd ciągły	2 A
Masa	20 g
Montaż	szyna DIN
Napięcie zasilania	12 V DC, 24 V DC
Odpowiedni silnik	Bezszcotkowy DC

Peak current	3
Rodzaj sterowania	Prędkość, Kierunek, Moment, Soft start/stop
Sygnał niski - logiczne 0	<1V = OFF
Sygnał wysoki - logiczne 1	>4V = ON
Wejście analogowe	0-5V lub 0-10V
Zakres ustawień prądu	0.1-3 A

