

F85RN WZMACNIACZ ŚWIATŁOWODOWY

Czujniki światłowodowe / fotokomórki
światłowodowe / fotoprzeźniki światłowodowe

F85RNP-J
Wzmacniacz światłowodowy podwójny wyświetlacz

- Duży podwójny wyświetlacz
- Wyjście PNP/NPN
- Funkcja zapobiegania wzajemnemu zakłócaniu się
- Kabel 2m lub złącze M8



OPIS PRODUKTU

The F85RN is a leading dual display fibre optic amplifier from Takex. It can simply be taught four separate teaching modes through the use of one set button. And with two large clear 4-digit, 7-segment LED displays and three raised buttons with positive click feedback, it makes mode setting even easier.

The F85RN is also equipped with an optical transmission type, mutual interference prevention function to suppress the interference between up to eight units.

The sensor comes with a QR code on the side of the amplifier to access a quick reference guide on your smartphone or tablet. This is useful when checking the manual or changing the settings while installing on site.

SPECYFIKACJA TECHNICZNA


Funkcja	Załącz, gdy jasno/ciemno
Materiał obudowa	Poliwęglan
Max. napięcie DC	24 V
Min. napięcie DC	12 V
Podłączenie elektryczne	Złącze M8 4-pinowe
Przełącznik załącz gdy jasno / załącz gdy ciemno	Nie
Stopień ochrony IP	IP40
Typ światła	LED czerwony




■ Detecting distance

Appearance	Model	Detecting distance (mm)	Detecting distance (cm)	Detecting distance (in)
	F85BC	500	330	160
	F75BC	1300	800	340

Optical transmission window



● M8 connector



Pin assignment	Pin No.	Description	F858NP-J Cable color(ø 1)
	1	12 to 24VDC	Brown
	4	PNP OUTPUT	Black
	2	NPN OUTPUT	White
	3	GND	Blue

ø 1 : For optional cables FBC-4R25/FBC-4R2L.

Do not use NPN and PNP output cable simultaneously. Be sure to use either output.